cannon

MKJ5 Series Connectors Miniature Circular Catalog



ENGINEERED FOR LIFE

Amazing things happen when great things connect

ITT Cannon is a leading global manufacturer of connector products serving international customers in the aerospace and defense, medical, energy, transportation and industrial end markets. Whether delivering critical specs to aircraft pilots, streaming data through communications satellites or enabling ultrasound technology that gives an expectant mother the first glimpse of her unborn child, Cannon connects the world's most important information with the people who need it.

No one is more qualified to help meet mission-critical requirements and equip military personnel than ITT Cannon. With 100 years of interconnect excellence and seven decades of global presence in the Defense Industry, we are a committed partner among today's military equipment manufacturers. We continue to lead the market in interconnect solutions that support combat preparation and to meet the military's needs for adaptability, mobility and survivability. And we do so with one goal in mind: to get our soldiers back home safely.









A Century of Connections

In 2015, Cannon marked its 100th Anniversary of Innovation. Cannon products were used in the first "talking" movies and helped transmit the first messages back to earth when we landed on the moon. Today we proudly continue our legacy of innovating to connect the world and inspire the successes of the next century – because amazing things happen when great things connect.

Visit ittcannon.com to learn more.

About ITT

ITT is a diversified leading manufacturer of highly engineered critical components and customized technology solutions for the energy, transportation and industrial markets. Building on its heritage of innovation, ITT partners with its customers to deliver enduring solutions to the key industries that underpin our modern way of life. This work is made possible by the talent and innovation of committed ITT employees in more than 35 countries who create trusted products and brands such as Goulds Pumps, KONI shock absorbers, Cannon connectors and Enidine energy absorption devices. Founded in 1920, ITT is headquartered in White Plains, N.Y. For more information, visit itt.com



www.ittcannon.com

Our connector portfolio remains one of the most extensive in the industry, providing customers with a reliable and cost-effective range of interconnect solutions.

Visit **ittcannon.com** to learn more.



















Table of Contents

MKJ Miniature Circular Connectors
Coupling Styles
Markets & Applications
We Connect Aerospace & Defense Industry with Mission Critical Data & Signal Transmission 8
Product Overview - MKJ5 Triple Start
MKJ5 Contact Arrangements & Layouts
MKJ5 Plug (Banded & Accessory Thread)
MKJ5 Receptacle In-Line, Box Mount/Square Flange, Jam Nut Rear Panel Mount
MKJ5 Receptacle In-Line (Banded & Accessory Thread)
MKJ5 Receptacle Box Mount/Square Flange (Banded & Accessory Thread)
MKJ5 Receptacle Jam Nut Rear Panel Mount (Banded & Accessory Thread)
MKJ5 Receptacle Box Mount/Square Flange, Jam Nut Rear Panel Mount (Potted, PCB & Solder Cup)
MKJ5 Receptacle Box Mount/Square Flange (Potted, PCB & Solder Cup)
MKJ5 Receptacle Jam Nut Rear Panel Mount (Potted, PCB & Solder Cup)
MKJ5 Weight Charts
MKJ Accessories
Cables to Outfit MKJ Connectors
About ITT Cannon
Product Safety Information
Meet Some of our Most Innovative Connectors



MKJ Series Connectors 71% weight and 52% size reduction in an industry-leading quick disconnect*

ITT Cannon continues its tradition of innovation with the MKJ line of miniature circular connectors. Bringing together a unique combination of design, functionality and flexibility, Cannon's MKJ Series offers proven, reliable and cost-effective interconnect solutions that enable critical communication, navigation and high speed data transmission—at half the size and weight of traditional ones. Choose from UNC thread, double start, triple start, bayonet and breakaway coupling methods in a cost-efficient, lightweight and highly engineered design.





MKJ0 UNC Thread

MKJ1 Double Start



MKJ3 Bayonet



MKJ4 Breakaway



MKJ5 Triple Start



Key Features

- 71% weight and 52% size reduction without the loss of reliability*
- Available in rear-release crimp, PC tail or solder cup contacts
- Shells and jam nuts available in aluminum alloy or corrosion resistant stainless steel
- Up to 2,000 mating cycles
- Environmentally sealed using fluorosilicone material for the front interfacial seal and rear wire sealing grommet
- RoHS Compliant

A Wide Range of Coupling Styles

The wide range of coupling options available for the MKJ Series allows compatible connectors to meet your demands even in the harshest environments.



Coupling	MKJ0 UNC Thread	MKJ 1 Double Start	MKJ 3 Bayonet	MKJ 4 Breakaway	MKJ 5 Triple Start			
Markets & Segments	Defense, Aerospace, Medical, Industrial, Commercial							
Hardware	Aluminum/ Stainless Steel	Aluminum/ Stainless Steel	Aluminum/ Stainless Steel	Aluminum/ Stainless Steel	Aluminum/ Stainless Steel			
EMI Shielding Effectiveness	40dB Attenuation, 100MHz to 1000MHz							
Mating Cycles	2000	2000	250 Aluminum 2000 Stainless Steel	2000	500			
RoHS Compliant	Available							
Materials	Shells - Aluminum Alloy or Stainless Steel Insulators - Thermoplastic Seals - Fluorosilicone Contacts - Copper Alloy with gold over nickel plating							

Product Performance

MKJ Series Performance								
Contact Size	#23 #20HD #16 #12							
Spacing	.076"	.106"	.170"	.230"				
Contact Type	Rear Crimp, Solder Cup, PCB Mount							
Current Rating	5 Amps 7.5 Amps 13 Amps 23 Amps							
Wire Accommodation	#22 - #28 AWG	#20 - #24 AWG	#16 - #20 AWG	#12 - #14 AWG				
DWV Voltage (VAC)	750 VAC	1000 VAC	1800 VAC	1800 VAC				
Insulation Resistance		5000 Megaohm	s RMS Sea					
Operating Temperature		-65°C to +1	75°C					
Contact Resistance		8 Milliohms M	aximum					
Shock/Vibration		300g / 3	7g					
Clocking Position	Master Key and 2 Secondary Keys. 6 Clocking Positions							
Housing Materials		Aluminum and Stainless Steel						
Receptacle Mounting		Jam Nut, Square Fla	ange, In-Line					



*When compared to the 38999 layouts with size 22 contacts Specifications and dimensions subject to change

Markets & Applications

Cannon MKJ Miniature Circular Connectors are designed for soldier-worn systems, military equipment, industrial and medical applications...and so much more.




Key Applications

- Sensors
- Satellites
- Instrumentation
- Missile systems
- Avionic systems
- Soldier technology
- UAVs / unmanned systems
- Navigation & telemetry equipment
- Medical test & diagnostic equipment
- Ruggedized computers
- Hand-held communication equipment
- Commercial & military aircraft electronics
- Industrial equipment

Highlights

- Versatile and proven for use in **military**, **industrial and medical applications** where safety and reliability are critical
- A number connectors in the MKJ Series offer a **2,000 mating cycle**, making them the perfect solution for ruggedized computers and hand-held communications equipment
- Multiple coupling mechanisms enable connectivity for navigation and telemetry applications
- Plugs and receptacles are **environmentally sealed** for use in the harshest environments
- Teflon nickel, black zinc nickel and olive drab cadmium plating maintain robust reliability for 500 hours of salt spray
- RoHS Compliant plating and part numbers available



We Connect the Aerospace & Defense Industry with Mission Critical Data & Signal Transmission

At half the size and weight of traditional harsh environment connectors, Cannon's MKJ5 Triple Start miniature circular interconnect offers superior vibration resistance and EMI prevention, without the loss of reliability or performance. MKJ5 Triple Start meets mission critical requirements for extended cycles in robust shock and vibration environments and is fully intermateable with other miniature equivalents. As part of Cannon's proven and versatile MKJ product line, MKJ5 Triple Start shares many of the attributes that make it one of the most lightweight and reliable sets of miniature circular connectors on the market.

Why ITT Cannon

With more than 100 years of interconnect excellence and seven decades of global presence in the defense industry, no one is more qualified to support mission critical electronic, communication and control applications than ITT Cannon. We are a committed partner among today's military equipment manufacturers and continue to lead the market in connector reliability and performance, even in the harshest environments.





Product Overview MKJ5 Triple Start

Part of the MKJ family of miniature circular connectors, ITT Cannon's innovative MKJ5 features threaded coupling with high density size 23 machined contacts for crimp and PCB. Its unique triple-start threaded coupling mechanism allows MKJ5 to quickly connect and disconnect, up to 500 cycles, while maintaining performance under sustained shock and vibration conditions. The MKJ5 also offers flexibility in configuration options for connectivity, multiple keying positions, and rear accessory threads or integral band platforms. It meets customer requirements for extended cycles in robust shock and vibration environments through its high-reliability internal ratchet mechanism system and is one of the most lightweight and reliable miniature circular connectors on the market.



Smaller, lighter packaging and high reliability under vibration make Cannon's MKJ5 miniature circular connectors well-suited for a variety of electronic, communication and control applications for military and commercial aircraft, rotor craft, launch vehicles, unmanned vehicles, ground vehicles and heavy equipment.

Specifications							
Contact Type	Rear Crimp, Solder Cup, PCB Mount	Insulation Resistance	5,000 Megaohms RMS Sea				
	Size 23 (0.076" spacing),	Operating Temperature	-65°C to +175°C				
Contact Spacing	Size 20HD (0.106" spacing),	Contact Resistance	8 Milliohms Maximum				
	Size 16 (0.170" spacing), Size 12 (0.230" spacing)	Shock/Vibration	300g / 37g				
		EMI Shielding Effectiveness	40dB Attenuation, 100MHz to 1000MHz				
Wire Accommodation	Size 23 #22 - #28 AWG, Size 20HD #20 - #24 AWG, Size 16 #16 - #20 AWG,	Coupling	Rotating Triple Start Coupling Nut				
		Receptacle Mounting	Jam Nut, Flange, In-Line				
	Size 12 #12 - #14 AWG	Durability	500 Mating Cycles				
	Size 23 5 Amps, Size 20HD 7.5 Amps,	Layouts	See Available Layout on Pages 10-11				
Contact Rating	Size 16 13 Amps,		Shells - Aluminum Alloy or Stainless Steel				
	Size 12 23 Amps		Insulators - Thermoplastic				
	Size 23 750 VAC,	Materials	Seals - Fluorosilicone				
DWV Voltage (VAC)	Size 20HD 1000 VAC, Size 16 1800 VAC,		Contacts - Copper alloy with gold over nickel plating				
	Size 12 1800 VAC		Canted Spring - Stainless Steel				


*When compared to the 38999 layouts with size 22 contacts


Dimensions shown in inches (mm)

Specifications and dimensions subject to change



MKJ5 Contact Arrangements & Layouts





Note: Pin insert front side shown for reference only. Socket insert is a mirror image.



MKJ5 Contact Arrangements & Layouts

Contact Arrangements							
Laurant	Contacts						
Layout	Size 16						
8-1	1						2001
10-2	2		$\begin{pmatrix} 2 \\ 0 \\ 0 \end{pmatrix}$	(0^{12})	$\begin{pmatrix} 0 & 2 \\ 0 & 0 \\ 0 & 0 \end{pmatrix}$	$\begin{pmatrix} 6 & \mathbf{O} & 2 \\ \mathbf{O} & 7 & \mathbf{O} \\ \mathbf{O} & \mathbf{O} & \mathbf{O} \\ \mathbf{O} & \mathbf{O} & \mathbf{O} \end{pmatrix}$	$\left(\begin{smallmatrix} {}^{9}\mathbf{O} & \mathbf{O} & \mathbf{O} \\ {}^{9}\mathbf{O} & \mathbf{O} & \mathbf{O} \\ {}^{1}2\mathbf{O} & \mathbf{O} & \mathbf{O}^{1}0 \end{smallmatrix}\right)$
11-4	4	8-1 Layout	10-2 Layout	04 3 11-4 Layout	12-5 Layout	15-7 Layout	18-12 Layout
12-5	5	- ayout	10-2 Layout	TI-4 Layout	12-5 Layout	13-7 Layout	16-12 Layout
15-7	7						
18-12	12						




Note: Pin insert front side shown for reference only. Socket insert is a mirror image.

ENGINEERED FOR LIFE

Dimensions shown in inches (mm)

Specifications and dimensions subject to change

MKJ5 Plug Banded & Accessory Thread







How to Order – MKJ5 Plug

Banded & Accessory Thread

Product	MKJ5 (Triple	Start) MKJ5 A 6 F 11-19 P A **
Class:	A -	Environmental Plug with Banding/Overmolding Attachment
	В -	Environmental Plug with Threaded Accessory Attachment
Shell Style:	6 -	Straight Plug
Material/Plating:	C -	Aluminum/Anodize, Black
	F -	Aluminum/Electroless Nickel (RoHS)
	К -	Stainless Steel/Passivated (RoHS)
	Τ-	Aluminum/Teflon Nickel (RoHS)
	W -	Aluminum/Olive Drab Cadmium
	Y -	Stainless Steel/Electroless Nickel, Black (RoHS)
	Ζ-	Aluminum/Zinc Nickel, Black (RoHS)
	N -	Stainless Steel/Electroless Nickel (RoHS)
Shell Size/Contact		See Available Layouts on Pages 10–11
Arrangement:		
Contact Style:	Ρ-	Pin, Crimp, Removable
, i i i i i i i i i i i i i i i i i i i	S -	Socket, Crimp, Removable
	Ε-	Pin, Solder Cup, Potted, Non-removable
	F -	Socket, Solder Cup, Potted, Non-removable
Shell Clocking	Α-	Normal
	B, C, D, E, F	Alternatives
Modification Codes:	- F0	Less Contacts ("F0" not stamped on the connector, but must be included on the P.O.)
	- F256	Stainless Steel Hood (Socket contact only)
	- 518	Potted connectors with water immersion testing (10 ⁻⁴ Helium leak tested)

Consult factory for other modification codes



engineered for life

MKJ5 Plug Banded & Accessory Thread

				ions	
Shell Size	ØA	ØB	C Thread	D Thread Accessory UNEF-2A	
8 (0.691	0.317	.50001P3L-TS-2B	.3750-32	EMI SPRING C THREAD
9 (0.787	0.397	.56251P3L-TS-2B	.4375-28	
10 0	0.826	0.473	.62501P3L-TS-2B	.5000-28	
11 (0.916	0.519	.68751P3L-TS-2B	.5625-24	
12 (0.982	0.585	.75001P3L-TS-2B	.6250-24	
15	1.097	0.687	.93751P3L-TS-2B	.7500-20	
18	1.290	0.884	1.12501P3L-TS-2B	.9375-20	
19	1.311	0.884	1.18751P3L-TS-2B	.9375-20	COUPLING NUT,
			MASTER KEY OBOO OBOO OBOO OBOO OBOO OBOO OBOO OB		ACCESSORY THREAD VERSION


For all Shell Sizes and Clockings, the Master Keyway remains stationary at top dead center, with minor keys rotating to achieve alternate clocking positions.


Cable Plug Barrel Clocking Dimensions								
MKJ5 PLUG BARREL CLOCKING	Position	K1°	K2°					
MASTER KEY	A (Normal)	150°	210°					
KI°	В	75°	210°					
K2° (С	95°	230°					
	D	140°	275°					
	E	75°	275°					
	F	95°	210°					



MKJ5 Receptacle

In-Line, Box Mount (Square Flange), Jam Nut Rear Panel Mount Banded & Accessory Thread





MKJ5 Jam Nut Receptacle – Rear Panel Mount (Shown with Banding/Overmolding Attachment)

Dimensions shown in inches (mm) Specifications and dimensions subject to change

www.ittcannon.com



How to Order – MKJ5 Receptacle

In-Line, Box Mount (Square Flange), Jam Nut Rear Panel Mount Banded & Accessory Thread

Product	MKJ5 (Triple	Start) MKJ5 A 7 F 11-19 P A **
Class:	A -	Environmental Receptacle with Banding/
	Β-	Environmental Receptacle with Threaded Accessory Attachment
Shall Styles	1	In Line Decentede
Shell Style:	1 - 2 -	In-Line Receptacle ————————————————————————————————————
	7 -	Jam Nut Receptacle-Rear Panel Mount
	/ -	
Material/Plating:	C -	Aluminum/Anodize, Black
	F -	Aluminum/Electroless Nickel (RoHS)
	K -	Stainless Steel/Passivated (RoHS)
	Τ-	Aluminum/Teflon Nickel (RoHS)
	W -	Aluminum/Olive Drab Cadmium
	Y -	Stainless Steel/Electroless Nickel, Black (RoHS)
	Z -	Aluminum/Zinc Nickel, Black (RoHS)
	N -	Stainless Steel/Electroless Nickel (RoHS)
Shell Size/Contact Arrangement:		See Available Layouts on Pages 10–11
Analigement.		
Contact Style:	P -	Pin, Crimp, Removable
	S -	Socket, Crimp, Removable
	E -	Pin, Solder Cup, Potted, Non-removable
	F -	Socket, Solder Cup, Potted, Non-removable
Shell Clocking:	A -	Normal
	B, C, D, E, F	Alternatives
Modification Codes:	- F0	Less Contacts ("F0" not stamped on the connector, but must be included on the P.O.)
	- F256	Stainless Steel Hood (Socket contact only)
	- 518	Potted connectors with water immersion testing (10 ⁻⁴ Helium leak tested)
		-


Consult factory for other modification codes





MKJ5 Receptacle

In-Line Banded and Accessory Thread




For all Shell Sizes and Clockings, the Master Keyway remains stationary at top dead center, with minor keys rotating to achieve alternate clocking positions.


Cable Receptacle In-Line Shell Clocking Dimensions								
MKJ5 SHELL CLOCKING	Position	K1°	K2°					
MASTER RETWAT	A (Normal)	150°	210°					
	В	75°	210°					
Kr	С	95°	230°					
K2°	D	140°	275°					
	E	75°	275°					
	F	95°	210°					




MKJ5 Receptacle Box Mount (Square Flange) Banded and Accessory Thread

	Receptacle Box Mount Dimensions									
Shell Size	ØA	В	C, Basic Typ	D Thread	ØE	ØF +.003	G Thread, Accessory (UNEF-2A)	H, Basic	ØJ	ØK
8	1.150	0.850	0.660	.50001P3L-TS-2A	0.317	0.094	.3750-32	0.660	0.520	
9	1.230	0.913	0.723	.56251P3L-TS-2A	0.397	0.094	.4375-28	0.723	0.584	
10	1.330	0.975	0.785	.62501P3L-TS-2A	0.473	0.094	.5000-28	0.785	0.653	0.094
	1.410	1.039	0.848	.68751P3L-TS-2A	0.519	0.094	.5625-24	0.848	0.718	
12	1.500	1.099	0.909	.75001P3L-TS-2A	0.585	0.094	.6250-24	0.909	0.775	
15	1.750	1.288	1.058	.93751P3L-TS-2A	0.687	0.128	.7500-20	1.058	0.961	
18	2.000	1.475	1.255	1.12501P3L-TS-2A	0.884	0.128	.9375-20	1.255	1.140	0.128
19	2.094	1.537	1.327	1.18751P3L-TS-2A	0.884	0.128	.9375-20	1.327	1.230	








For all Shell Sizes and Clockings, the Master Keyway remains stationary at top dead center, with minor keys rotating to achieve alternate clocking positions.

Receptacle Box Mount Shell Clocking Dimensions								
	Position	K1°	K2°					
	A (Normal)	150°	210°					
$(\Phi) $	В	75°	210°					
κι° κτ²°	С	95°	230°					
	D	140°	275°					
	E	75°	275°					
	F	95°	210°					






MKJ5 Receptacle

Jam Nut – Rear Panel Mount Banded and Accessory Thread

	Cable Receptacle Jam Nut Dimensions									
Shell Size	DIA. ØA	ØB FLATS	C Flat	D Thread	E THREAD (UN-2A)	ØF	G THREAD ACCESSORY (UNEF-2A)	H Flat	۵J	
8	0.760	0.730	0.535	.50001P3L-TS-2A	.5625-32	0.317	.3750-32	0.543	0.572	F THREAD
9	0.880	0.850	0.661	.56251P3L-TS-2A	.6875-28	0.397	.4375-28	0.669	0.698	
10	0.880	0.850	0.661	.62501P3L-TS-2A	.6875-28	0.473	.5000-28	0.669	0.698	
	0.955	0.925	0.721	.68751P3L-TS-2A	.7500-28	0.519	.5625-24	0.729	0.760	
12	1.060	1.035	0.784	.75001P3L-TS-2A	.8125-28	0.585	.6250-24	0.792	0.822	
15	1.203	1.173	0.970	.93751P3L-TS-2A	1.0000-28	0.687	.7500-20	0.978	1.010	
18	1.389	1.359	1.147	1.12501P3L-TS-2A	1.1875-28	0.884	.9375-20	1.155	1.198	
19	1.450	1.420	1.221	1.18751P3L-TS-2A	1.2500-28	0.884	.9375-20	1.223	1.385	
							PANEL THICKNESS			

For all Shell Sizes and Clockings, the Master Keyway remains stationary at top dead center, with minor keys rotating to achieve alternate clocking positions.


Cable Receptacle Jam Nut Shell Clocking Dimensions								
MKJ5 SHELL CLOCKING	Position	K1°	K2°					
NASTER KETWAT	A (Normal)	150°	210°					
Kſ°	В	75°	210°					
K2°	С	95°	230°					
	D	140°	275°					
	E	75°	275°					
	F	95°	210°					



MKJ5 Receptacle

MKJ5 Jam Nut Receptacle with PCB Mount Socket Insert

Box Mount (Square Flange), Jam Nut Rear Panel Mount Potted, PCB & Solder Cup




MKJ5 Jam Nut Receptacle – Rear Panel Mount – PCB Mount CONTACT, SOCKET (CONTACT, PIN AVAILABLE)




How to Order – MKJ5 Receptacle Box Mount (Square Flange), Jam Nut Rear Panel Mount Potted, PCB & Solder Cup

Product	MKJ5 (Triple	Start) MKJ5 C 2 F 11-19 B A **
Class:	C -	Potted Receptacle-PC/Flex/Solder
Shell Style:	2 -	Box Mount Receptacle (Square Flange)
	7 -	Jam Nut Receptacle-Rear Panel Mount
Material/Plating:	C -	Aluminum/Anodize, Black
	F -	Aluminum/Electroless Nickel (RoHS)
	Κ-	Stainless Steel/Passivated (RoHS)
	Τ-	Aluminum/Teflon Nickel (RoHS)
	W -	Aluminum/Olive Drab Cadmium
	Y -	Stainless Steel/Electroless Nickel, Black (RoHS)
	Z -	Aluminum/Zinc Nickel, Black (RoHS)
	N -	Stainless Steel/Electroless Nickel (RoHS)
Shell Size/Contact Arrangement:		See Available Layouts on Pages 10–11
Contact Style:	В -	Pin, PC Tail, .109 Extension, Potted, Non-removable
2	D -	Socket, PC Tail, .109 Extension, Potted, Non-removable
	E -	Pin, Solder Cup, Potted, Non-removable
	F -	Socket, Solder Cup, Potted, Non-removable
Shell Clocking:	A -	Normal
	B, C, D, E, F	Alternatives
Modification Codes:	- F256	Stainless Steel Hood (Socket contact only)
	- 518	Potted connectors with water immersion testing (10 ⁻⁴ Helium leak tested)
		Consult factory for other modification codes




MKJ5 Receptacle

Box Mount (Square Flange) Potted, PCB & Solder Cup



For all Shell Sizes and Clockings, the Master Keyway remains stationary at top dead center, with minor keys rotating to achieve alternate clocking positions.


Receptacle Box Mount Shell Clocking Dimensions							
MKJ5 SHELL CLOCKING	Position	K1°	K2°				
	A (Normal)	150°	210°				
$(\Phi) $	В	75°	210°				
Ki ^o Kz ^o	С	95°	230°				
	D	140°	275°				
	E	75°	275°				
	F	95°	210°				






MKJ5 Receptacle

Jam Nut Rear Panel Mount Potted, PCB & Solder Cup



For all Shell Sizes and Clockings, the Master Keyway remains stationary at top dead center, with minor keys rotating to achieve alternate clocking positions.

Receptacle Jam Nut Shell Clocking Dimensions								
MKJ5 SHELL CLOCKING	Position	K1°	K2°					
MASTER KETRAT-	A (Normal)	150°	210°					
Kŕ	В	75°	210°					
K2°	С	95°	230°					
	D	140°	275°					
	E	75°	275°					
	F	95°	210°					





MKJ5 Weight Charts

	MKJ5 Connector Weight in Grams								5 Connector ght in Grams		
Pin Layout	Plug	Jam Nut Receptacle Crimp	Jam Nut Receptacle PCB	Square Flange Receptacle Crimp	Square Flange Receptacle PCB	Socket Layout	Plug	Jam Nut Receptacle Crimp	Jam Nut Receptacle PCB	Square Flange Receptacle Crimp	Square Flange Receptacle PCB
8-1P	8.4	6.9	7.0	6.7	5.7	8-IS	8.8	7.2	7.0	6.2	6.4
8-23P	8.3	6.7	6.6	6.7	5.5	8-23S	8.8	7.2	7.2	7.4	6.1
8-4P	8.1	6.8	6.7	6.8	5.6	8-4S	8.7	7.1	7.4	7.6	6.3
8-6P	8.2	6.9	7.0	6.9	5.7	8-6S	8.7	7.1	7.5	6.1	6.4
8-7P	8.2	7.0	6.9	7.0	5.8	8-7S	8.8	7.2	7.0	7.2	5.9
9-1P	10.7	9.2	9.2	7.0	7.9	9-IS	11.7	9.8	9.8	7.6	8.5
9-25P	10.8	9.3	9.2	7.1	8.0	9-25S	.4	9.5	9.6	7.5	8.2
9-10P	11.1	9.2	9.2	7.0	7.9	9-10S	11.3	9.4	9.4	7.2	8.1
10-2P	12.9	9.8	9.9	8.7	9.2	10-2S	13.0	9.8	9.9	9.6	10.0
10-28P	13.2	9.9	10.1	9.2	9.9	10-285	15.8	10.3	10.4	10.0	10.5
10-13P	12.4	9.6	9.7	8.2	8.6	10-13S	12.7	10.2	9.8	8.9	9.4
11-4P	15.1	11.0	12.0	10.2	11.2	-4S	15.4	13.0	13.4	11.2	12.2
-2 0P	15.0	11.5	12.2	9.7	10.7	-2 0S	15.3	12.8	13.7	.	12.0
- 9P	15.3	11.2	12.0	9.4	10.4	- 9S	15.7	12.0	13.0	10.2	11.2
12-2P	17.1	13.7	15.2	11.6	12.0	12-2S	18.1	14.8	16.8	13.3	13.5
12-5P	17.4	13.7	16.1	2.	13.0	12-55	17.7	15.2	17.6	3.	14.0
12-26P	17.3	13.2	13.2	10.4	11.2	12-26S	17.4	13.5	14.4	10.3	11.2
15-2P	20.5	20.2	21.8	16.9	19.5	15-2S	22.1	21.8	23.3	18.6	21.0
15-3P	21.6	21.3	22.9	17.9	20.6	I 5-3S	22.3	22.9	24.4	19.7	22.1
15-7P	22.0	21.6	23.1	18.5	20.9	15-7S	22.9	24.0	25.5	21.1	23.5
15-220P	20.9	21.1	23.9	18.4	21.8	15-220S	23.5	23.5	26.0	21.4	23.7
15-37P	20.2	20.2	20.4	17.0	19.6	15-37S	21.4	22.4	23.9	19.2	21.6
18-12P	30.8	32.4	32.6	27.8	31.5	18-12S	32.4	34.1	32.6	29.6	32.5
18-5P	32.2	33.8	33.2	29.4	32.9	18-55	33.2	34.9	33.4	30.4	33.3
18-235P	30.3	31.1	29.3	28.8	30.8	18-2355	32.1	33.6	32.8	28.1	31.7
18-55P	27.5	28.0	28.0	25.3	27.0	18-55S	30.2	30.4	29.0	26.0	28.5
19-85P	31.0	29.8	29.5	28.4	30.9	19-855	32.1	32.6	35.7	28.8	35.6



MKJ Accessories

Format Sheet-Tooling and Contacts MKJ

Crimp Contacts

 Pin Contacts (Size 23)
 030-9649-000

 Socket contacts (Size 23)
 031-9750-000

Contact Area Plating:

50 Micro inches Gold over Nickel Accommodates Sizes #22-28 AWG Wire

Contact Crimp Tool Locator 995-0002-293 995-0002-297





Contact Insertion/Extraction Tools

Insertion Tool	995-0002-295
Extraction Tool	995-0002-294


Banding Tools Hand banding Tool 1/8" bands (100 pk)

995-0002-298

995-0002-299

Banding Tools

PART NUMBER	USE ON JAMNUT SIZE / PN
317-2187-000	MKJ1 (6) MKJ0 (7)
317-2187-001	MKJ1 (7) MKJ0 (9)
317-2187-002	MKJ1 (9)
317-2187-003	MKJ1 (13)
317-2187-006	MKJ0 (6)
317-2187-007	MKJ0 (12)







Backshells



Backshell Designator Table

Backshell Designator	1	2	3	2	1	I	5	(5	7	7	٤	3
Shell Style	МКЈО, МКЈ1, МКЈ3, МКЈ4	МКЈО, МКЈ1, МКЈ3, МКЈ4	MKJ5	MKJ0, MKJ1, MKJ3, MKJ4	MKJ5	MKJ0, MKJ1, MKJ3, MKJ4	MKJ5	МКЈО, МКЈ1, МКЈ3, МКЈ4	MKJ5	MKJ0, MKJ1, MKJ3, MKJ4	MKJ5	MKJ0, MKJ1, MKJ3, MKJ4	MKJ5
Shell Size	(05) Straight	(06) Straight	(08) Straight	(07) Straight	(09) Straight	(08) Straight	(10) Straight	(09) Straight	(11) Straight	(10) Straight	(12) Straight	(12) Straight	(13) Straight

Heat Shrink Boot

Material: Fluid resistant elastomer

Adhesive: Polyamide hot melt

MKJ Heat Shrink Boot P/N's - Straight					
ITT P/N					
980-2010-017					
980-2010-018					
980-2010-019					

MKJ Heat Shrink Boot P/N's - 90°				
Shell Size	ITT P/N			
5, 6, 7	980-2010-020			
8, 9	980-2010-021			
10, 11, 12, 13	980-2010-022			

Metal Dust Caps

MKJ Aluminum Dustcap Designator- Talking Dog





cannon

Cables to Outfit Your MKJ Connector Value-Added MKJ Series Cabling Solutions from ITT Cannon



Let ITT Cannon complete your MKJ solution with our custom cable products. A complement to the reduction in size of the connectors is the reduction in weight and thickness in cabling. Choose from several available options to help customize your application. Improving on our high reliability connectors, we offer overmolds that are suitable for military requirements in harsh environments.





About ITT Cannon

ITT Inc. is a diversified leading manufacturer of highly engineered critical components and customized technology solutions for industrial end-markets in energy infrastructure, electronics, aerospace and transportation. Building on its heritage of innovation, ITT partners with its customers to deliver enduring solutions to the key industries that underpin our modern way of life. Founded in 1920, ITT is headquartered in White Plains, N.Y., with employees in more than 35 countries and sales from a total of 125 countries.

Our connector portfolio remains the most extensive in the industry, offering a reliable and cost effective range of interconnect solutions. Continuous investment in technology and research & development have enabled ITT to provide new, innovative products and solutions to markets including:

- Commercial Aviation
- Defense
- Oil & Gas
- Industrial
- Medical
- Space Exploration

When you specify a Cannon connector, you can rely on products that are designed, developed, and manufactured to the highest quality and reliability standards. This tradition of excellence is based on ITT's corporate culture of operating its businesses under the principles of Six Sigma. At ITT, Six Sigma is not just a quality philosophy but a complete corporate culture that drives the entire business. Our Value Based Management and Value Based Product Development systems are two cornerstones that allow for the development of both leadership and product engineering principles, ensuring our industry leading products are developed to the accepted market driven lead times. These principles have allowed ITT to become the market leader in all of our business portfolios.

Six Sigma Manufacturing

ITT Cannon operates manufacturing facilities in the United States, Germany, Italy, Mexico, China and Japan, allowing ITT to offer global capabilities to our customers. Our fullyintegrated, world class facilities use the latest manufacturing technologies including automated and robotic maching centers, Super Market manufacturing cells, Kanban pull systems, and automated, electrical, mechanical and optical test and inspection equipment. The combination of our manufacturing strength and our advanced manufacturing facilities allows ITT to offer products at market driven prices. Our capabilities, especially in robotics, computerized precision tooling, Kaizen Project Management, Six Sigma tools and testing, give ITT the most optimized global manufacturing footprint in the interconnect industry.

The Custom Difference

As the industry leader in harsh environment interconnect applications, ITT's world class engineering teams will work directly with our customers to design and develop cost effective solutions for their applications. In many cases we may modify one of our standard designs to ensure a highly reliable solution where timing is critical. When custom connectors are required, we collaborate with clients and partners with a goal to design the most reliable, cost-effective solution possible. As professional consultants, our Engineering teams will provide a thorough systems and mechanical analysis of any proposed solution. These analyses provide our customers with sophisticated electrical signal and mechanical characterizations to determine the best solution for their application.

RoHS Compliance Information

ITT has implemented a strict parts control plan for all ITT electronics plants worldwide that allows the Cannon product portfolio to meet the requirements of the European Union Directive 2002/95/EC better known as the Reduction of Hazardous Substances initiative. As appropriate, specific Cannon products may be ordered with an R prefix number which insures our customers will receive RoHS compliant parts for their commercial electronics applications and equipment. Since most RoHS hazardous substances center around specific metal plating and lead solder coatings, ITT's products for RoHS compliance are available in the following plating finishes: electroless nickel, stainless steel, anodize over aluminum and gold plating. It should be noted that gold plating would be recommended as the replacement for tin-lead solder when ordering board mount connectors.





Product Safety

1. Material Content and Physical Form

Electrical connectors do not usually contain hazardous materials. They contain conducting and non-conducting materials and can be divided into two groups.

- a) Printed circuit types and low cost audio types which employ all plastic insulators and casings.
- b) Rugged, Fire Barrier and High Reliability types with metal casings and either natural rubber, synthetic rubber, plastic or glass insulating materials. Contact materials vary with type of connector and also application and are usually manufactured from either: Copper, copper alloys, nickel, alumel, chromel or steel. In special applications, other alloys may be specified.

ACAUTION

2. Fire Characteristics And Electric Shock Hazard There is no fire hazard when the connector is correctly wired and used within the specified parameters. Incorrect wiring or assembly of the connector or careless use of metal tools or conductive fluids, or transit damage to any of the component parts may cause electric shock or burns. Live circuits must not be broken by separating mated connectors as this may cause arcing, ionization and burning. Heat dissipation is greater at maximum resistance in a circuit. Hot spots may occur when resistance is raised locally by damage, e.g. cracked or deformed contacts, broken strands of wire. Local overheating may also result from the use of the incorrect application tools or from poor quality soldering or slack screw terminals. Overheating may occur if the ratings in the product Data Sheet/ Catalog are exceeded and can cause breakdown of insulation and hence electric shock. If heating is allowed to continue it intensifies by further increasing the local resistance through loss of temper of spring contacts, formation of oxide film on contacts and wires and leakage currents through carbonization of insulation and tracking paths. Fire can then result in the presence of combustible materials and this may release noxious fumes. Overheating may not be visually apparent. Burns may result from touching overheated components.

3. Handling

Care must be taken to avoid damage to any component parts of electrical connectors during installation and use. Although there are normally no sharp edges, care must be taken when handling certain components to avoid injury to fingers. Electrical connectors may be damaged in transit to the customers, and damage may result in creation of hazards. Products should therefore be examined prior to installation/use and rejected if found to be damaged.

4. Disposal

Incineration of certain materials may release noxious or even toxic fumes.

5. Application

Connectors with exposed contacts should not be selected for use on the current supply side of an electrical circuit, because an electric shock could result from touching exposed contacts on an unmated connector. Voltages in excess of 30 V ac or 42.5 V dc are potentially hazardous and care should be taken to ensure that such voltages cannot be transmitted in any way to exposed metal parts of the connector body. The connector and wiring should be checked, before making live, to have no damage to metal parts or insulators, Dimensions shown in inches (mm)

Specifications and dimensions subject to change

no solder blobs, loose strands, conducting lubricants, swarf, or any other undesired conducting particles. Circuit resistance and continuity check should be made to make certain that there are no high resistance joints or spurious conducting paths. Always use the correct application tools as specified in the Data Sheet/Catalog. Do not permit untrained personnel to wire, assemble or tamper with connectors. For operation voltage please see appropriate national regulations.

Important General Information

(i) Air and creepage paths/Operating voltage. The admissible operating voltages depend on the individual applications and the valid national and other applicable safety regulations. For this reason the air and creepage path data are only reference values. Observe reduction of air and creepage paths due to PC board and/or harnessing.

(ii) Temperature

All information given are temperature limits. The operation temperature depends on the individual application.

(iii) Other important information

ITT Cannon continuously endeavors to improve their products. Therefore, Cannon products may deviate from the description, technical data and shape as shown in this catalog and data sheets.

ITT Cannon, is a division of ITT Inc. who manufactures the highest quality products available in the marketplace; however these products are intended to be used in accordance with the specifications in this publication. Any use or application that deviates from the stated operating specifications is not recommended and may be unsafe. No information and data contained in this publication shall be construed to create any liability on the part of ITT Cannon. Any new issue of this publication shall automatically invalidate and supersede any and all previous issues.





Meet Some of Our Most Innovative Connectors

D-Subminiature Connectors

Originally designed for aircraft radio systems, Cannon's D-Subminiature Connector became the first multi-purpose interconnect solution of its kind, ideal for multiple markets and applications. From rocket launches and satellite systems, to rugged military transports and commercial avionics, the D-Subminiature's versatility has made this Cannon invention the most widely used connector in the world.



Rack & Panel Connectors

Pioneered by Cannon during the 1930s, our Rack & Panel Connectors offer an unmatched variety of shell configurations and insert arrangements, as well as materials, plating and contact options. Today, we are recognized as an industry leader, offering an unparalleled range of off-the-shelf and custom Rack & Panel products to align with customer needs.



Microminiature Connectors

Developed first by Cannon in the 1960s, Microminiature Connectors offer high performance and reliability with exceptional versatility. Available in rectangular, circular and strip-style configurations, our highly engineered Microminiature connector products meet critical customer demands in multiple applications across the Aerospace & Defense industry





Notes:



Connect with your ITT Cannon representative today or visit us at www.ittcannon.com



Whether communicating with our soldiers in the field or with first responders saving lives, ITT Cannon connects vital information with those who need it.



CHINA—Shenzhen City +86.755.2726.7888

JAPAN—Kanagawa +81.462.57.2010

USA—Watertown, CT +1.860.274.9681 **GERMANY—Weinstadt** +49.7151.699.0

KOREA—Seoul +82.2.7027111 HONG KONG

+852.2732.2720 **TAIWAN—Taipei** +886.2.25452020 ITALY—Lainate +39.02938721 UK—Basingstoke +44.1256.311200

USA—Irvine, CA +1.800.854.3028

The "ITT Engineered Blocks" symbol, "Engineered for life," "ITT" and "Cannon" are registered trademarks of ITT Inc. Specification and other data are based on information available at the time of printing, and are subject to change without notice.